

2 SC 955	Njr	Si-N	Uni, 20/15V, 0,05A, 0,15W, 150MHz	8a	TO-106	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 SC 956	Njr	Si-N	Uni, 50/40V, 0,05A, 0,15W, 200MHz	8a	TO-106	BC 546	7a	BC 167, BC 182, BC 237, BC 547, ++
2 SC 957	Son	Si-N	VHF, 30/30V, 0,1A, 0,36W, 700MHz	2a	TO-1	BF 198, BF 199	7d	BF 225, BF 310, BF 311, BF502, BF 505, ++
2 SC 959(S)	Nec, Mic	Si-N	Uni, 120/80V, 0,7/1,2A, 0,7W, 100MHz S=hi-rel Version	(2SA606) 2a	TO-39	(BC 141) ⁷	2a	BC 300, BSY 55...56, 2N1893(A), 2N2102, ++
2 SC 960		Si-N	=2SC959:	(2SA607) 43m	=TO-37	(2SC4135) ⁴	30j	(2SC2384, 2SC2690(A), 2SD1382) ⁴
2 SC 961	old	Si-N	LFS P, 120/90V, 7A, 60W, 13MHz	23a	TO-3	BD 245 C	18j	BD 245C, BD 550, 2N5633, 2SD1046, ++
2 SC 962		Si-N	=2SC961: 100/80V	23a	TO-3	BD 245 C	18j	BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 SC 963	Fui	Si-N	Uni, 35/25V, 0,05A, 0,25W, 200MHz, hFE=70	2a	TO-18	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 SC 964		Si-N	=2SC963: hFE=100	2a	TO-18	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 SC 965		Si-N	=2SC963: 45/30V, -<300ns	2a	TO-18	BC 546	7a	BC 167, BC 182, BC 237, BC 547, ++
2 SC 966	Fui	Si-N	Uni, 30/20V, 0,2A, 0,5W, 70MHz	2a	TO-18	BC 337	7a	BC 337...338, BC 635, BC 637, BC 639, ++
2 SC 967	Fui	Si-N	Uni, 30/20V, 0,5A, 0,5W, 70MHz	2a	TO-18	BC 337	7a	BC 337...338, BC 635, BC 637, BC 639, ++
2 SC 968	Fui	Si-N	Uni, 50/30V, 0,5A, 0,5W, 70MHz	2a	TO-18	BC 337	7a	BC 337, BC 637, 2SC3939, 2SD1226, ++
2 SC 969	Fui	Si-N	Uni, 50/30V, 0,2A, 0,5W, 60MHz	2a	TO-18	BC 337	7a	BC 337, BC 637, 2SC3939, 2SD1226, ++
2 SC 970	Fui	Si-N	Uni, 50/30V, 0,5A, 0,5W, 70MHz, -<950ns	2a	TO-18	BC 337	7a	BC 337, BC 637, 2SC3939, 2SD1226, ++
2 SC 971	Fui	Si-N	Uni, 50/30V, 0,5A, 1W, 70MHz	2a°	=TO-18°	BC 337	7a	BC 337, BC 637, BC 639, 2SC1225...26, ++
2 SC 972	Say	Si-N	Uni, 70/70V, 0,4A, 0,6W, 80MHz	2a	TO-39	BC 141	2a	BC 140...141, BC 300...301, 2N1711, ++
2 SC 973(A)	Mit	Si-N	UHF Drv,Out, 40V, 0,5A, 1200MHz, PQ=4W(500MHz/13V)	55r				BLW 43, BLW 80, 2N5945
2 SC 974	Mit	Si-N	UHF Drv,Out, 40V, 1A, 1200MHz, PQ=6W(500MHz/13V)	55r				BLU 97, BLX 68, BLV 53
2 SC 975(A)	Mit	Si-N	UHF Drv,Out, 40V, 1,5A, 1200MHz, PQ=8W(500MHz/13V)	55r				BLW 44, BLW 81, 2N5946
2 SC 976	Mit	Si-N	UHF Drv,Out, 55/35V, 0,4A, PQ=1,1W(1GHz/28V)	55r				BFT 99, BLV 91, MRF 817
2 SC 977	Mit	Si-N	UHF Drv,Out, 55/35V, 0,6A, 1300MHz, PQ=3W(1GHz/28V)	55r				BLU 99
2 SC 978	Mit	Si-N	UHF Drv,Out, 55/35V, 1,2A, PQ=5,5W(1GHz/28V)	55r				-
2 SC 979	Tos	Si-N	Uni, 70/50V, 0,1A 0,3W, 250MHz, 25/430ns	(2SA499) 2a	TO-18	BC 546	7a	BC 174, BC 182, BC 190, BC 546, ++
2 SC 979 A		Si-N	=2SC979: 100/70V	2a	TO-18	2SC2632	7c(9mm)	2SC2240, 2SC2459, 2SC3245(A), 2SC3248
2 SC 980(G,GTm)	Tos	Si-N	Uni, 70/50V, 0,1A, 0,2W, 400MHz, 25/630ns GTM: 0,4W, TO-92	7c	TO-98, -92	BC 546	7a	BC 174, BC 182, BC 190, BC 546, ++
2 SC 980 A		Si-N	=2SC980: 90/70V	7c	TO-98, -92	2SC2632	7c(9mm)	2SC2240, 2SC2459, 2SC3245(A), 2SC3248
2 SC 981	Tos	Si-N	LFS P, 100V, 5A, 25W, 10MHz	22a	TO-66	BD 243 C	17j	BD 243C, BD 543C, BD 953, 2SD613, ++
2 SC 982(TM)	Tos	Si-N-Darl	LFS, 40/40V, 0,3/0,4A, 0,4W, hFE>5000	7c	TO-98, -92	(BC 879) ¹³	7c	BC 517, BC 617, MPS-A25...29, 2SC4009
2 SC 983	Tos	Si-N	Vid, 250/150V, 0,05A, 0,6W, 120MHz	9b		BF 420 A	7c	BF 298...299, BF 422, BF 483, BFR 88...89
2 SC 984	Hit	Si-N	Uni, 50/50V, 0,5A, 0,35W, 230MHz	(2SA565) 2a	TO-1	BC 639	7c	BC 337, BC 637, 2SC3939, 2SD1226, ++
2 SC 984 H		Si-N	=2SC984: 100/50V	2a	TO-1	BC 639	7c	BC 639, BCX 24, 2SC4414, 2SD667, 2SD1226
2 SC 985(A)	Nec	Si-N	UHF, In, 20/15V, 0,04A, 3,2GHz, Gp=9,5dB(2GHz)	51s				BFO 59...60, BFO 70...71, BFT 97
2 SC 986	Nec	Si-N	UHF Drv,Out, 35/20V, 0,2A, 2,56GHz	55r				BFT 98, BFO 68
2 SC 987(A)	Nec	Si-N	UHF, 20/15V, 0,03A, 4,5GHz, F=8/Gp=5dB(4GHz)	51s				BFO 69, BFO 71, BFO 85, BFR 14, BFR 91
2 SC 988(A,B)	Nec	Si-N	UHF, In, 20/15V, 0,03A, 3GHz, Gp=25dB(500MHz) 2SC988: F<2,5dB, A: F<2dB, B: <1,5dB(500MHz)	5g	TO-72			BFR 15, BFT 66...67, BFS 55
2 SC 989	Nec	Si-N	UHF, 20/12V, 0,05A, 3GHz	24d				BFT 65, BFO 72
2 SC 990	Nec	Si-N	UHF P, 50/25V, 2A, 400MHz, PQ=13,4W(400MHz/18V)	55s				BLW 94, BLX 94, MRF 323
2 SC 991	Tos	Si-N	VHF Drv,Out, 36V, 0,4A, 500MHz, PQ=1,3W(175MHz/12V)	2a	TO-39			BFO 42, BFS 51, BFR 98, BLW 16, BLY 61
2 SC 992	Tos	Si-N	VHF Drv,Out, 36V, 0,6A, 500MHz, PQ=2,5W(175MHz/12V)	2a	TO-39			BFS 22, BFW 46, BLY 33, MRF 237, 2N3924
2 SC 993	Fui	Si-N	Uni, 25/15V, 0,2A, 0,2W, 400MHz	2a	TO-46	(BC 546) ⁸	7a	BSW 41, BSY 62...63, 2N706A, 2N4124, ++
2 SC 994	Tos	Si-N	VHF Os,Drv, 36/15V, 0,1A, PQ=0,95W(175MHz/13,5V)	2a	TO-39			BFW 16...17, BFX 55
2 SC 995	Tos	Si-N	Vid, 300/300V, 0,15A, 0,8W, 100MHz	2a	TO-39	BF 259	2a	BF 259, BF 659, BFR 59, BFR 89, 2N5058
2 SC 996		Si-N	=2SC995:	43a	=TO-37	(BF 459) ⁴	14h	(BF 417, BF 459, BF 617, BF 758...)+ ⁴
2 SC 997	Tos	Si-N	HF,IF, 40/30V, 25mA, 0,15W, 600MHz	5k	TO-72	BF 198, BF 199	7d	BF 198...199, BF 224...225, BF 310...311, ++
2 SC 998	Tos	Si-N	VHF Drv,Out, 40/20V, 0,4A, PQ>1W(175MHz/12,6V)	2a	TO-39			BFO 42, BFS 51, BFR 98, BLW 16, BLY 61
2 SC 999	Tos	Si-N	TV-HA, 1500/700V, 1,5A, 50W, 1MHz	23a	TO-3	(BU 208 A)	23a	BU 204...206, 2SD575, 2SD818
2 SC 999 A		Si-N	=2SC999: 1500/650V, 2,5A, 4MHz	23a	TO-3	BU 208 A	23a	BU 204...206, 2SD575, 2SD818
2 SC 1000	Tcs	Si-N	Uni, In, 55/50V, 0,1A, 0,2W, 80MHz; F<3dB	(2SA493) 7c	TO-98	BC 550	7a	BC 414, BC 550, 2SC2240, 2SC2459, ++
2 SC 1000 GTM		Si-N	=2SC1000: 60/50V, 0,4W	7c	TO-92	2SC2632	7c(9mm)	2SC2240, 2SC2459
2 SC 1001	Tos	Si-N	UHF Drv,Out, 40/20V, 0,5A, PQ>1,2W(470MHz/12,6V)	2a(E=case)	TO-39			BFS 50, MRF 629, 2N3948, 2SC2852
2 SC 1002	Tos	Si-N	UHF P, 36/18V, 1A, 700MHz, PQ=3W(470MHz/12,6V)	49a	TO-60			-
2 SC 1003		Si-N	UHF P, 36/18V, 2A, 600MHz, PQ=6W(470MHz/12,6V)	49a	TO-60			-
2 SC 1004	Tos	Si-N	TV-HA/VA, 1100/700V, 0,5A, 50W, 5,5MHz	23a	TO-3			BU 204...206, 2SC1167, 2SD1095
2 SC 1004 A		Si-N	=2SC1004: 1500/800V	23a	TO-3			BU 205...206, 2SD575, 2SD818
2 SC 1005	Tos	Si-N	TV-HA, 1100/600V, 5A, 50W, 3MHz	23a	TO-3	BU 208 A	23a	BU 207...209, 2SC1413, 2SD380(A), ++
2 SC 1005 A		Si-N	=2SC1005: 1400/600V	23a	TO-3	BU 208 A	23a	BU 208...209, 2SD380(A), 2SD792, 2SD954++
2 SC 1006	Nec	Si-N	Uni, In, 50/40V, 0,03A, 0,3W, 90MHz	(2SA579) 2a	TO-18	BC 550	7a	BC 184, BC 414, BC 550, 2SC2240, ++
2 SC 1007	Nec	Si-N	Uni, 60/40V, 0,2A, 0,3W, 250MHz	2a	TO-18	BC 546	7a	BC 174, BC 182, BC 190, BC 546, ++
2 SC 1008	Nec, Mic	Si-N	Uni, 80/60V, 0,7A, 0,8W, 75MHz, 120/300ns	2a	TO-39	BC 141	2a	BC 140...141, BC 300...301, 2N1889...90, ++
2 SC 1008 A		Si-N	=2SC1008: 100/80V	2a	TO-39	BC 141	2a	BC 141, BC 300, 2N1889...90, 2N2102, ++
2 SC 1009(A)	Nec	Si-N	SMD, HF In, 50/25V, 0,05A, 250MHz, F=2,5dB(1MHz)	35a	SOT-23	BC 846	35a	BC 846...847, BCW 71...72, BCW 81, ++
2 SC 1010	Nec	Si-N	Uni, In, 50/40V, 0,03A, 0,3W, 90MHz, F<3dB	(2SA578) 2a	TO-18	BC 550	7a	BC 184, BC 414, BC 550, 2SC2240, ++
2 SC 1011	Mit	Si-N	VHF A,Drv,Out, 40/20V, 0,75A, PQ=3W(150MHz)	51r	TO-131			BLW 17, 2SC1405
2 SC 1012(Z)	Mat, Mic	Si-N	Vid, 165V, 0,06A, 0,75W, >80MHz, Z=hi-rel Version	2a	TO-39	BF 259	2a	BF 257...259, BF 657...659, 2N5058...59
2 SC 1012 A		Si-N	=2SC1012: 250V	2a	TO-39	BF 259	2a	BF 258...259, BF 658...659, 2N5058...59
2 SC 1013	Mit	Si-N	P, 35/20V, 1,5A, 7W, 70MHz, <200/1200ns,	(2SA623) 13n	=TO-202	(2SC4135) ⁴	30j	(BD 507, BD 517, BD 525, BD 839...)+ ⁵
2 SC 1014		Si-N	=2SC1013: 50/40V	(2SA624) 13n	=TO-202	(2SC4135) ⁴	30j	(BD 509, BD 519, BD 527, BD 841...)+ ⁵
2 SC 1015	Mit	Si-N	UHF P, 40/18V, 3A, 1200MHz, PQ=14W(450MHz/13,5V)	55r				BLW 15, BLX 69
2 SC 1016	Mit	Si-N	UHF Drv,Out, 35V, 0,5A, PQ=1,3W(500MHz/12V)	51r	TO-131			BLW 12, BLX 66
2 SC 1017	Mit	Si-N	AM Out, 75/35V, 1A, 200MHz, PQ=0,06W(27MHz/12V)	13n	=TO-202			-
2 SC 1018	Mit	Si-N	AM Out, 75/35V, 1A, 200MHz, PQ=1,4W(27MHz/12V)	13n	=TO-202			-
2 SC 1019	Mit	Si-N	UHF P, 60/35V, 4A, PQ=28W(500MHz/28V)	60c				2N6104
2 SC 1020		Si-N	UHF P, 60/35V, 8A, PQ=45W(500MHz/28V)	60c				-
2 SC 1021	Mit	Si-N	VHF P, 60/40V, 6A, 500MHz, PQ=45W(90MHz/28V)	55r				(BLX 15)
2 SC 1022	Mit	Si-N	VHF P, 60/40V, 6A, 500MHz, PQ=45W(150MHz/28V)	55r				-
2 SC 1023	Fui	Si-N	HF, 25/20V, 25mA, 0,15W, 200MHz	7c	TO-92	BF 255	7d	BF 240...241, BF 254...255, BF 594...595, ++
2 SC 1024	Say	Si-N	TV-VA, 60/50V, 3A, 25W, 8MHz	22a	TO-66	BD 243 C	17j	BD 241A, BD 935, 2N4232, 2SC2352, ++
2 SC 1025	Say	Si-N	S P, TV-HA, 200/120V, 3A, 25W, 8MHz	22a	TO-66	BU 406	17j	BU 406...408, 2SC1025, 2SD1136, 2SD1159
2 SC 1026	Fui	Si-N	HF, 25/20C, 25mA, 0,15W, 200MHz, F=2,5dB(1MHz)	7c	TO-92	BF 255	7d	BF 240...241, BF 254...255, BF 594...595, ++
2 SC 1027	Say	Si-N	S P, 250/80V, 6A, 50W	23a	TO-3	BU 608	23a	BU 606...608, BUX 18(A...C), 2SC2769, ++
2 SC 1030	Hit	Si-N	L F P, 150/80V, 6/10A, 50W, 10MHz	(2SA756) 23a	TO-3	2SC3263	18j	BD 245D, 2N3442, 2SD551, 2SD1046, ++
2 SC 1031	Fui, Nec	Si-N	S P, 300/300V, 2A, 30W, 15MHz, <5/15µs	22a	TO-66	BU 406	17j	BUX 67A...C, 2N3584, 2SC1504, 2SC2023, ++
2 SC 1032	Fui	Si-N	HF, 25/20V, 25mA, 0,15W, 200MHz	7c	TO-92	BF 255	7d	BF 240...241, BF 254...255, BF 594...595, ++
2 SC 1033	Mat, Mic	Si-N	Nixie, Vid, 200/150V, 25mA, 0,3W, 150MHz	2a	TO-18	BF 420 A	7c	BF 298...299, BF 422, BF 483, 2SC3467, ++
2 SC 1033 A		Si-N	=2SC1033: 250/200V	2a	TO-18	BF 420 A	7c	BF 298...299, BF 420, BF 422, BF 483, ++
2 SC 1034	Son	Si-N	S P, TV-HA, 1100V, 1A, 25W, 5MHz, sat<5V(0,75A)	22a	SOT-9			BU 505, 2SD470, 2SD948, 2SD1492
2 SC 1035	Say	Si-N	VHF/UHF Inp In, 30/15V, 20mA, 700MHz, F=6dB(800MHz)	5g	TO-104	2SC2570 A	7f	BF 377...378, BF 689, BF 763, 2N2857, ++
2 SC 1036	Say	Si-N	VHF/UHF Mx.Os, 30/15V, 20mA, 700MHz	5g	TO-104	2SC2570 A	7f	BF 377...378, BF 689, BF 763, 2N2857, ++
2 SC 1037	Nec	Si-N	VHF P, 60/40V, 4/10A, 250MHz, PQ=33W(160MHz/28V)	49a	TO-60			-